



PS/2 Keyboard/Mouse Power Select	JP1	Digital I/O Power Select	JP15	
+5V (default)	1-2 On	+5V_standby (default)	1-2 On	
+5V_standby	2-3 On	+5V	2-3 On	
Backlight Power Select	JP2	Digital I/O Output State: DIO 0-3 (JP16), DIO 4-7 (JP17)		
+12V (default)	1-2 On	+5V or +5V_standby (default)	1-2 On	
+5V	2-3 On	GND	2-3 On	
Panel Power Select	JP11	Power-on Select	JP13	
+12V	1-2 On	Power-on via Power Button (default)	1-2 On	
+5V	3-4 On	Power-on via AC Power; Power-on via WOL after G3	2-3 On	
+3V (default)	5-6 On	Mini PCIe Signal Select	JP12	
USB Power Select: 0-1 (JP6), 2-3/10-11 (JP8), 4-5 (JP5)		PCIe (default)	1-4-7-10, 2-5-8-11 On	
+5V (default)	1-2 On	mSATA	2-5-8-11 3-6-9-12 On	
+5V_standby	2-3 On	SATA DOM Power Select	JP18	
Clear CMOS Data	JP9	GND (default)	1-2 On	
Normal (default)	1-2 On	+5V	2-3 On	
Clear CMOS Data	2-3 On			
Switch 1	1 On	1 Off	2 On	2 Off
LVDS Channel and bpp Select	Single LVDS	Dual LVDS	VESA (24bpp)	JEIDA or VESA (18bpp)

Note:
SATA1 supports SATA DOM.

Battery Notice



Battery Usage

The lithium ion battery powers the real-time clock and CMOS memory. It is an auxiliary source of power when the main power is shut off.



Safety Measures

- Danger of explosion if battery incorrectly replaced.
- Replace only with the same or equivalent type recommend by the manufacturer.
- Dispose of used batteries according to local ordinance.



Mesure de Sécurité de l'usage de Batterie

Batterie:

- Danger d'explosion si la batterie n'est pas correctement remplacée.
- Remplacez seulement avec le même type ou équivalent recommandé par le fabricant.
- Traitez des batteries usées selon le règlement local.