



PCIE1/M.2 B Key PCIE Signal Select	JP3
PCIE1 (default)	1-2, 4-5, 7-8, 10-11 On
M.2 B key PCIE	2-3, 5-6, 8-9, 11-12 On

LVDS Panel Power Select	JP8
+12V	1-2 On
+5V	3-4 On
+3.3V (default)	5-6 On

LVDS Backlight Power Select	JP9
+3.3V (default)	1-2 On
+5V	2-3 On

LCD/Inverter Power Select	JP10
+12V (default)	1-2 On
+5V	2-3 On

SATA 1/M.2 B Key SATA Signal Select	JP4
SATA 1 (default)	1-2, 4-5, 7-8, 10-11 On
M.2 B key SATA	2-3, 5-6, 8-9, 11-12 On

COM Port RS232/Power Select	COM1 (JP2), COM2 (JP5)
RS232 (default)	1-3 (RI-), 2-4 (DCD-) On
RS232 with power	3-5 (+5V), 4-6 (+12V) On

Clear CMOS Data	JP6
Normal (default)	1-2 On
Clear CMOS Data	2-3 On

M.2 Signal Select	JP1
SATA (default)	1-2 On
PCIE	2-3 On

Note:

1. AL171: Single 12V +/-10% DC.
2. AL173: Wide Range 15~36V.
3. The right angle power connector and vertical type power connector are optional. Please contact your sales representative for more information.

Battery Notice



Battery Usage

The lithium ion battery powers the real-time clock and CMOS memory. It is an auxiliary source of power when the main power is shut off.



Safety Measures

- Danger of explosion if battery incorrectly replaced.
- Replace only with the same or equivalent type recommended by the manufacturer.
- Dispose of used batteries according to local ordinance.



Mesure de Sécurité de l'usage de Batterie

Batterie:

- Danger d'explosion si la batterie n'est pas correctement remplacée.
- Remplacez seulement avec le même type ou équivalent recommandé par le fabricant.
- Traitez des batteries usées selon le règlement local.